Jackery Explorer 240

	Р	OWER STATION SPECIFICATION		WHAT'S IN THE BOX
		Capacity	240Wh	
		Continuous Output	200W	
		Peak Output	400W	
		Charged with AC Adapter	5.5 H	
		Charged with 12V Car Outlet	6.5 H	
		Charged with Solar Panel	4.5 H (1*100W Panels)	
		Battery Lifecycles	After 1000 cycles, \geq 80% capacity remains	1* Explorer 240 Portable Power Station
		Input Ports	8mm DC Input (x1):19V/3.42A (support 12~30V)	(240Wh)
Phone	50" TV	Output Ports	AC Output (x1): 110VAC, 60Hz, 200W/ 400W Surge Peak Car Port Output(x1); 12V/10A USB-A Outputs (x2):5V/2.4A DC Input (x1) :12V-30V(65W Max)	6
24Charges (lphone 8)	2.3H (120W)	Product Weight	6.6lbs (3KG)	1* Car Charger Cable
	-	Dimensions	9.05 x 5.24 x 7.87in	
H	[Ö]	Operating Usage Temperature	32°~104°F (0~40°C)	
Drone	Camera	Battery Management System	6 Types of Protection	
4Charges (60W)	11Charges (10W)	Steady Power (Pure Sine Wave) AC Outlet	√	
C		Temperature Control Probes	x2	1* AC Charger Cable
Light	Electric Blanket	Fire Resistance Rating	UL 94-V0	
40H (5W)	4H (52W)	Shock-Resistant Level	/	Jackery
	8	Compatibility with Electrical Appliances	/	
		Noise Level	≤46db	USER MANUAL Jackery Explorer 240
Laptop 3.5Charges (Macbook Pro13)	Fan 15H	APP Intelligent Control	/	Married Avenue
		Waranty	2 Years	1* User Manual

